

## Digital SWR / WATT Meter

Nova Code: **TES-475**

- Reads Forward Power
- Reverse Power
- SWR Reading
- Powered by x2 AAA or USB Port
- Switchable back Light



Specifications	TES-475
Frequency Range	125 to 470 mHz (VHF/UHF only)
Power Range	0 -120W +/- 5%
Centre Calibrated	145 mHz + 435 mHz
Insertion Loss	0.3dB or Lower
Impedance	50 $\Omega$
Connector	UHF Female
Dimension (W x H x D) in mm	70 x 78 x 30
Weight	220 g

Specification subject to change without notice. Issue 1