

Digital SWR / WATT Meter

Nova Code: **TES-475A**

- Reads Forward Power
- Reverse Power
- SWR Reading
- Powered by x2 AAA or USB Port
- Switchable back light



Specifications	TES-475A
Frequency Range	1.6 – 60 MHz
Power Range	0 -200 W + 5%
Centre Calibrated	30 MHz
Insertion Loss	0.3dB or Lower
Impedance	50 Ω
Connector	UHF Female
Dimension (W xH x D) in mm	70 x 78 x 30
Weight	220g

Specification subject to change without notice. Issue 1